

# **PacketCable™ 1.5 Specifications**

## **Signaling Extension MIB**

### **PKT-SP-MIB-EXSIG1.5-C01-191120**

**CLOSED**

#### **Notice**

This PacketCable specification is the result of a cooperative effort undertaken at the direction of Cable Television Laboratories, Inc. for the benefit of the cable industry and its customers. You may download, copy, distribute, and reference the documents herein only for the purpose of developing products or services in accordance with such documents, and educational use. Except as granted by CableLabs® in a separate written license agreement, no license is granted to modify the documents herein (except via the Engineering Change process), or to use, copy, modify or distribute the documents for any other purpose.

This document may contain references to other documents not owned or controlled by CableLabs. Use and understanding of this document may require access to such other documents. Designing, manufacturing, distributing, using, selling, or servicing products, or providing services, based on this document may require intellectual property licenses from third parties for technology referenced in this document. To the extent this document contains or refers to documents of third parties, you agree to abide by the terms of any licenses associated with such third-party documents, including open source licenses, if any.

## DISCLAIMER

This document is published by Cable Television Laboratories, Inc. ("CableLabs®").

CableLabs reserves the right to revise this document for any reason including, but not limited to, changes in laws, regulations, or standards promulgated by various agencies; technological advances; or changes in equipment design, manufacturing techniques, or operating procedures described, or referred to, herein. CableLabs makes no representation or warranty, express or implied, with respect to the completeness, accuracy, or utility of the document or any information or opinion contained in the report. Any use or reliance on the information or opinion is at the risk of the user, and CableLabs shall not be liable for any damage or injury incurred by any person arising out of the completeness, accuracy, or utility of any information or opinion contained in the document.

This document is not to be construed to suggest that any affiliated company modify or change any of its products or procedures, nor does this document represent a commitment by CableLabs or any cable member to purchase any product whether or not it meets the described characteristics. Nothing contained herein shall be construed to confer any license or right to any intellectual property, whether or not the use of any information herein necessarily utilizes such intellectual property. This document is not to be construed as an endorsement of any product or company or as the adoption or promulgation of any guidelines, standards, or recommendations.

## Document Status Sheet

<b>Document Control Number:</b>	PKT-SP-MIB-EXSIG1.5-C01-191120			
<b>Document Title:</b>	Signaling Extension MIB			
<b>Revision History:</b>	I01 - Issued January 28, 2005 I02 - Issued August 12, 2005 I03 - Issued April 12, 2007 I04 - Issued June 24, 2009 I05 - Issued October 30, 2012 C01 - Closed November 20, 2019			
<b>Date:</b>	November 20, 2019			
<b>Status:</b>	<del>Work in Progress</del>	<del>Draft</del>	<del>Issued</del>	<b>Closed</b>
<b>Distribution Restrictions:</b>	<del>Author Only</del>	<del>CL/Member</del>	<del>CL/Member/Vendor</del>	<b>Public</b>

### Key to Document Status Codes:

<b>Work in Progress</b>	An incomplete document, designed to guide discussion and generate feedback that may include several alternative requirements for consideration.
<b>Draft</b>	A document in specification format considered largely complete, but lacking review by Members and vendors. Drafts are susceptible to substantial change during the review process.
<b>Issued</b>	A generally public document that has undergone Member and Technology Supplier review, cross-vendor interoperability, and is for Certification testing if applicable. Issued Specifications are subject to the Engineering Change Process.
<b>Closed</b>	A static document, reviewed, tested, validated, and closed to further engineering change requests to the specification through CableLabs.

### Trademarks

CableLabs® is a registered trademark of Cable Television Laboratories, Inc. Other CableLabs marks are listed at <http://www.cablelabs.com/certqual/trademarks>. All other marks are the property of their respective owners.

## Contents

<b>1</b>	<b>SCOPE.....</b>	<b>1</b>
1.1	PURPOSE OF THE DOCUMENT.....	1
1.2	REQUIREMENTS .....	1
<b>2</b>	<b>REFERENCES .....</b>	<b>1</b>
2.1	NORMATIVE REFERENCES .....	1
2.2	INFORMATIVE REFERENCES .....	2
2.3	REFERENCE ACQUISITION.....	2
<b>3</b>	<b>ABBREVIATIONS.....</b>	<b>3</b>
<b>4</b>	<b>REQUIREMENTS .....</b>	<b>3</b>
	<b>APPENDIX A LOOP VOLTAGE MANAGEMENT POLICIES.....</b>	<b>18</b>
	<b>APPENDIX B ACKNOWLEDGEMENTS .....</b>	<b>20</b>
	<b>APPENDIX C REVISION HISTORY .....</b>	<b>21</b>

# 1 SCOPE

## 1.1 Purpose of the Document

New objects that are being introduced beyond PacketCable 1.0 for Signaling MIBS are being grouped in this document so that the additional changes made can be tracked easily.

## 1.2 Requirements

Throughout this document, the words that are used to define the significance of particular requirements are capitalized. These words are:

"MUST"	This word means that the item is an absolute requirement of this specification.
"MUST NOT"	This phrase means that the item is an absolute prohibition of this specification.
"SHOULD"	This word means that there may exist valid reasons in particular circumstances to ignore this item, but the full implications should be understood and the case carefully weighed before choosing a different course.
"SHOULD NOT"	This phrase means that there may exist valid reasons in particular circumstances when the listed behavior is acceptable or even useful, but the full implications should be understood and the case carefully weighed before implementing any behavior described with this label.
"MAY"	This word means that this item is truly optional. One vendor may choose to include the item because a particular marketplace requires it or because it enhances the product, for example; another vendor may omit the same item.

# 2 REFERENCES

## 2.1 Normative References

In order to claim compliance with this specification, it is necessary to conform to the following standards and other works as indicated, in addition to the other requirements of this specification. Notwithstanding, intellectual property rights may be required to use or implement such normative references.

- [1] PacketCable 1.5 MTA Device Provisioning Specification, PKT-SP-PROV1.5-C01-191120, November 20, 2019, Cable Television Laboratories, Inc.
- [2] IETF STD 62, Simple Network Management Protocol Version 3 (SNMPv3), December 2002.
- [3] IETF RFC 2669, Cable Device Management Information Base for DOCSIS compliant Cable Modems and Cable Modem Termination Systems.
- [4] Data-Over-Cable Service Interface Specifications, DOCSIS 1.1, Operations Support System Interface, SP-OSSiv1.1-C01-050907, September 7, 2005, Cable Television Laboratories, Inc.
- [5] IETF STD 5, Internet Protocol, September 1981.
- [6] IETF RFC 2011, SNMPv2 Management Information Base for the Internet Protocol using SMIV2, November 1996.
- [7] IETF RFC 2863, The Interfaces Group MIB, June 2000.
- [8] eDOCSIS Specification, CM-SP-eDOCSIS-I30-191120, November 20, 2019, Cable Television Laboratories, Inc.

- [9] CableLabs Definition MIB Specification, CL-SP-MIB-CLABDEF-I12-160325, March 25, 2016, Cable Television Laboratories, Inc.
- [10] Data-Over-Cable Service Interface Specifications, DOCSIS 2.0, Operations Support System Interface Specification, CM-SP-OSSIV2.0-C01-081104, November 4, 2008, Cable Television Laboratories, Inc.
- [11] PacketCable 1.5 MTA MIB Specification, PKT-SP-MIB-MTA1.5-C01-191120, November 20, 2019, Cable Television Laboratories, Inc.
- [12] PacketCable 1.5 Signaling MIB Specification, PKT-SP-MIB-SIG1.5-C01-191120, November 20, 2019, Cable Television Laboratories, Inc.
- [13] PacketCable 1.5 MIBs Framework, PKT-SP-MIBS1.5-C01-191120, November 20, 2019, Cable Television Laboratories, Inc.
- [14] IETF RFC 2833, RTP Payload for DTMF Digits, Telephony Tones and Signals, May 2000.
- [15] PacketCable 1.5 Audio/Video Codecs Specification, PKT-SP-CODEC1.5-C01-191120, November 20, 2019, Cable Television Laboratories, Inc.
- [16] PacketCable 1.5 Network-Based Call Signaling Protocol Specification, PKT-SP-NCS1.5-C01-191120, November 20, 2019, Cable Television Laboratories, Inc.

## 2.2 Informative References

- [17] Data-Over-Cable Service Interface Specifications, Cable Modem to Customer Premise Equipment Interface Specification (CMCI), CM-SP-CMCI-C01-081104, November 4, 2008, Cable Television Laboratories, Inc.
- [18] IETF RFC 3417, Transport Mappings for the Simple Network Management Protocol (SNMP), December 2002.
- [19] IETF RFC 2579, Textual Conventions for SMIV2, April 1999.
- [20] IETF RFC 3410, Introduction and Applicability Statements for Internet-Standard Management Framework, December 2002.
- [21] IETF RFC 3411, An Architecture for Describing Simple Network Management Protocol (SNMP) Management Frameworks, December 2002.
- [22] IETF RFC 3412, Message Processing and Dispatching for the Simple Network Management Protocol (SNMP), December 2002.
- [23] IETF RFC 2821, Simple Mail Transfer Protocol, April 2001.
- [24] PacketCable 1.5 Dynamic Quality of Service Specification, PKT-SP-DQOS1.5-C01-191120, November 20, 2019, Cable Television Laboratories, Inc.
- [25] IETF RFC 3594, PacketCable Security Ticket Control Sub-Option for the DHCP CableLabs Client Configuration (CCC) Option, September 2003.
- [26] IETF RFC 2782, A DNS RR for specifying the location of services (DNS SRV), February 2000.
- [27] IETF RFC 3584, Coexistence between Version 1, Version 2, and Version 3 of the Internet-standard Network Management Framework, August 2003.
- [28] PacketCable 1.5 Management Event MIB Specification, PKT-SP-EVEMIB1.5-C01-191120, November 20, 2019, Cable Television Laboratories, Inc.

## 2.3 Reference Acquisition

CableLabs Specifications:

- Cable Television Laboratories, Inc., 858 Coal Creek Circle, Louisville, CO 80027; Phone +1-303-661-9100; Fax +1-303-661-9199; Internet: <http://www.cablelabs.com>.

- Internet Engineering Task Force (IETF) Secretariat c/o Corporation for National Research Initiatives, 1895 Preston White Drive, Suite 100, Reston, VA 20191-5434, Phone +1-703-620-8990, Fax +1-703-620-9071, Internet: [www.ietf.org/](http://www.ietf.org/)

### 3 ABBREVIATIONS

There are no abbreviations used in this document.

### 4 REQUIREMENTS

The PacketCable Extension Signaling MIB **MUST** be implemented as defined below.

```
PKTC-EN-SIG-MIB DEFINITIONS ::= BEGIN
```

```
IMPORTS
```

```
    MODULE-IDENTITY,
    OBJECT-TYPE,
    Unsigned32, BITS FROM SNMPv2-SMI
    ifIndex FROM IF-MIB
    SnmpAdminString
        FROM SNMP-FRAMEWORK-MIB
    TruthValue
        FROM SNMPv2-TC
    OBJECT-GROUP,
    MODULE-COMPLIANCE
        FROM SNMPv2-CONF
    pktcEnhancements
        FROM CLAB-DEF-MIB
    pktcNcsEndPntConfigEntry
        FROM PKTC-SIG-MIB;
```

```
pktcEnSigMib MODULE-IDENTITY
```

```
LAST-UPDATED "201210300000Z" -- October 30, 2012
```

```
ORGANIZATION "Cable Television Laboratories, Inc."
```

```
CONTACT-INFO
```

```
"Sumanth Channabasappa
```

```
Postal: Cable Television Laboratories, Inc.
```

```
858 Coal Creek Circle
```

```
Louisville, Colorado 80027-9750
```

```
U.S.A.
```

```
Phone: +1 303-661-9100
```

```
Fax: +1 303-661-9199
```

```
E-mail: mibs@cablelabs.com"
```

```
DESCRIPTION
```

```
"This MIB module enhances the basic management
objects defined for PacketCable Signaling
protocols by the MIB group pktcSigMib.
```

```
Acknowledgements:
```

```
Rodney Osborne - Arris Interactive
```

```
Eugene Nechamkin - Broadcom Corporation
```

```
Satish Kumar - Texas Instruments
```

```
Jean-Francois Mule - CableLabs
```

```
Copyright 1999-2012 Cable Television Laboratories, Inc.
```

```
All rights reserved."
```

```
REVISION "201210300000Z" -- October 30, 2012
```

## DESCRIPTION

"Revised Version includes ECNs  
MIB-EXSIG1.5-N-12.0689-2  
and published as part of PKT-SP-MIB-EXSIG1.5-I05-121030

REVISION "200906150000Z" -- June 15, 2009

## DESCRIPTION

"Revised Version includes ECNs  
MIB-EXSIG1.5-N-09.0569-2  
and published as part of PKT-SP-MIB-EXSIG1.5-I04-090624"

REVISION "200704120000Z"

## DESCRIPTION

"This revision is being published as part of the PacketCable  
Signaling MIBs I03 enhancements for PacketCable 1.5."

REVISION "200508120000Z"

## DESCRIPTION

"This revision is being published as part of the PacketCable  
Signaling MIBs enhancements for PacketCable 1.5."

::= { pktcEnhancements 2 }

--

-- Enhanced MIB Objects and Divisions.

--

```
pktcEnSigMibObjects      OBJECT IDENTIFIER
                        ::= { pktcEnSigMib 1 }
pktcEnSigDevConfigObjects OBJECT IDENTIFIER
                        ::= { pktcEnSigMibObjects 1 }
pktcEnNcsEndPntConfigObjects OBJECT IDENTIFIER
                        ::= { pktcEnSigMibObjects 2 }
pktcEnSigEndPntConfigObjects OBJECT IDENTIFIER
                        ::= { pktcEnSigMibObjects 3 }
pktcEnDcsEndPntConfigObjects OBJECT IDENTIFIER
                        ::= { pktcEnSigMibObjects 4 }
```

--

-- Enhanced Notification groups.

--

```
pktcEnSigNotificationPrefix OBJECT IDENTIFIER
                        ::= { pktcEnSigMib 2 }
pktcEnSigNotification OBJECT IDENTIFIER
                        ::= { pktcEnSigNotificationPrefix 0 }
pktcEnSigConformance OBJECT IDENTIFIER
                        ::= { pktcEnSigMib 3 }
pktcEnSigCompliances OBJECT IDENTIFIER
                        ::= { pktcEnSigConformance 1 }
pktcEnSigGroups OBJECT IDENTIFIER
                        ::= { pktcEnSigConformance 2 }
```

```
pktcEnNcsMinimumDtmfPlayout OBJECT-TYPE
    SYNTAX Unsigned32 (0 | 40..100)
```



```

UNITS "milliseconds"
MAX-ACCESS read-write
STATUS current
DESCRIPTION
    "This object defines the minimum playout time for
    the DTMF digit when IETF RFC 2833 DTMF Relay is used
    for the egress gateway.
    If the value set via this pktcEnNcsMinimumDtmfPlayout
    object is different from that specified in RFC2833 packet,
    then the MTA MUST use the maximum of the two values.
    For example:
    If the RFC 2833 packet specifies 23ms and if the object
    pktcEnNcsMinimumDtmfPlayout is set to 40ms then
    the egress gateway must use a value of 40ms.
    Similarly if the RFC 2833 packet specifies
    60 ms and if the object pktcEnNcsMinimumDtmfPlayout
    is set to 40ms then the egress gateway must use a
    value of 60 ms."
REFERENCE
    "PacketCable(tm) Codec Specification"
DEFVAL {0}
::= { pktcEnSigDevConfigObjects 1}

--
-- The following table enhances the NCS End Point Config Table
-- (pktcNcsEndPntConfigTable) defined in pktSigMib.
--
--
pktcEnNcsEndPntConfigTable OBJECT-TYPE
    SYNTAX      SEQUENCE OF PktcEnNcsEndPntConfigEntry
    MAX-ACCESS   not-accessible
    STATUS       current
    DESCRIPTION
        "This table augments pktcNcsEndPntConfigTable."
    ::= { pktcEnNcsEndPntConfigObjects 1 }

pktcEnNcsEndPntConfigEntry OBJECT-TYPE
    SYNTAX      PktcEnNcsEndPntConfigEntry
    MAX-ACCESS   not-accessible
    STATUS       current
    DESCRIPTION
        "An enhancement to pktcNcEndPntConfigTable - where each
        entry describes endpoint characteristics."
    AUGMENTS { pktcNcsEndPntConfigEntry }
    ::= { pktcEnNcsEndPntConfigTable 1 }

PktcEnNcsEndPntConfigEntry ::=
    SEQUENCE {
        pktcEnNcsEndPntQuarantineState INTEGER,
        pktcEnNcsEndPntHookState INTEGER,
        pktcEnNcsEndPntFaxDetection TruthValue,
        pktcEnNcsEndPntStatusReportCtrl INTEGER
    }

pktcEnNcsEndPntQuarantineState OBJECT-TYPE
    SYNTAX INTEGER {
        normal (1),
        notification (2),
        lockstep (3),

```

```

        extendedlockstep (4)
    }
    MAX-ACCESS    read-only
    STATUS        current
    DESCRIPTION
        "This object reflects the state of the Endpoint.
        When the endpoint is in notification, lockstep or
        'extended lockstep' states, the E-MTA MUST report the
        values of notification(2), lockstep(3) or extended lockstep
        (4), respectively. Else, the endpoint MUST report a value of
        normal(1).
        'Extended Lockstep' is defined as the state when the
        E-MTA is in the lockstep state for longer than 2 minutes.
        For more description about the states refer
        to the PacketCable Network Based Call signaling
        specification."
    REFERENCE
        "PacketCable(tm) Network-Based Call Signaling Protocol
        Specification,"
    ::= { pktcEnNcsEndPntConfigEntry 1 }

pktcEnNcsEndPntHookState    OBJECT-TYPE
    SYNTAX INTEGER {
        onHook                (1),
        onHookPlusNCSActivity (2),
        offHook                (3)
    }
    MAX-ACCESS    read-only
    STATUS        current
    DESCRIPTION
        "This object reflects the 'hook state' and 'NCS Activity'
        of an endpoint.
        'NCS Activity', by definition includes: an active
        timeout signal, active brief signal or existence of
        an NCS connection.
        The onHook(1) state indicates that the endpoint is
        'on hook' and the absence of 'NCS Activity' on that
        endpoint.
        The onHookPlusNCSActivity(2) indicates that the endpoint
        is 'on hook' and the presence of 'NCS Activity' on that
        endpoint.
        The offHook(3) state indicates that the endpoint is
        'off hook'."

    REFERENCE
        "PacketCable(tm) Network-Based Call Signaling Protocol Specification"
    ::= { pktcEnNcsEndPntConfigEntry 2 }

pktcEnNcsEndPntFaxDetection    OBJECT-TYPE
    SYNTAX TruthValue
    MAX-ACCESS    read-create
    STATUS        current
    DESCRIPTION
        "This MIB object is used to configure
        the distinctive fax calling tone (CNG) detection feature
        on an MTA endpoint with reference to the analog interface.
        When set to true, the MTA MUST enable the detection
        of CNG tones on the specific endpoint.
        When set to false, the MTA MUST disable the detection
        of CNG tones on the specific endpoint.
        If a connection already exists on the endpoint when this

```

MIB Object is modified, then the setting needs to take effect on the next connection."

```

    DEFVAL {false}
    ::= { pktcEnNcsEndPntConfigEntry 3}

pktcEnNcsEndPntStatusReportCtrl      OBJECT-TYPE
    SYNTAX INTEGER {
        unsupported                (1),
        reportActualStatus         (2),
        reportEndPointAsActive     (3)
    }
    MAX-ACCESS read-create
    STATUS      deprecated
    DESCRIPTION
        "This MIB object is be used to control
        the Endpoint Status Reporting, if the feature is
        supported by the MTA and is configurable.
        The term 'Endpoint Status Reporting' refers to any
        information that the MTA may provide to External
        Systems for use in a particular reporting mechanism
        (Ex: Home Alarm Systems). The definition of the External
        Systems and reporting mechanism are beyond the scope
        of this definition (In the example of Home Alarm Systems,
        this MIB Object will allow Management Stations to
        temporarily disable outage reporting on an EndPoint
        during planned downtime).
        If supported, the MTA MUST:
        - reflect the actual Endpoint status when the value
          is set to 'reportActualStatus(2)'
        - reflect the EndPoint status as being active when the
          value is set to 'reportEndPointAsActive(3)',
          irrespective of the actual status.
        If unsupported, the MTA MUST set this value to
        'unsupported(1)' and reject any attempt to set
        this MIB object using SNMP SET to any other value."
    ::= { pktcEnNcsEndPntConfigEntry 4}

pktcEnEndPntInfoTable      OBJECT-TYPE
    SYNTAX      SEQUENCE OF PktcEnEndPntInfoTableEntry
    MAX-ACCESS   not-accessible
    STATUS       current
    DESCRIPTION
        "This table includes any additional information
        associated with PacketCable EndPoints.
        The number of entries in this table represents the
        number of available PacketCable EndPoints."
    ::= { pktcEnNcsEndPntConfigObjects 2 }

pktcEnEndPntInfoTableEntry  OBJECT-TYPE
    SYNTAX      PktcEnEndPntInfoTableEntry
    MAX-ACCESS   not-accessible
    STATUS       current
    DESCRIPTION
        "An entry in this table MUST be created for each
        PacketCable EndPoint.
        The index needs to be the corresponding index in the ifTable
        for the associated PacketCable EndPoint."
    INDEX { ifIndex }
    ::= { pktcEnEndPntInfoTable 1 }

```

```

pktcEnEndPntInfoTableEntry ::=
    SEQUENCE {
        pktcEnEndPntFgnPotSupport    BITS,
        pktcEnEndPntFgnPotDescr     SnmpAdminString,
        pktcEnEndPntClrFgnPotTsts    BITS,
        pktcEnEndPntRunFgnPotTsts    BITS,
        pktcEnEndPntFgnTestValidity BITS,
        pktcEnEndPntFgnTestResults  BITS
    }

pktcEnEndPntFgnPotSupport OBJECT-TYPE
    SYNTAX BITS {
        fgnPotDetection (0),
        hazardousFgnPotDetection (1)
    }
    MAX-ACCESS read-only
    STATUS current
    DESCRIPTION
        "This MIB object indicates the capabilities of the MTA to
        detect various conditions related to the presence of
        foreign potential on an endpoint.
        The MTA MUST set a value of '1' for each bit corresponding
        to a supported functionality and a value of '0' for each
        bit corresponding to an unsupported functionality."
    ::= { pktcEnEndPntInfoTableEntry 1 }

pktcEnEndPntFgnPotDescr OBJECT-TYPE
    SYNTAX SnmpAdminString
    MAX-ACCESS read-only
    STATUS current
    DESCRIPTION
        "This MIB object provides information related to the
        various tests for each detection mechanism supported by
        the MTA. While the actual contents are vendor-specific,
        the recommended format is:
        [<Capability>:<Test References>:<Other Info>]...
        Example:
        <fgnPotDetection>:<test XYZ, Reference 'Document'>:<NA>;
        <hazardousFngPotDetection>:<Test ABC, References>:<NA>
        "
    ::= { pktcEnEndPntInfoTableEntry 2 }

pktcEnEndPntClrFgnPotTsts OBJECT-TYPE
    SYNTAX BITS {
        clrFgnPotentialResults (0),
        clrHazardousPotResults (1)
    }
    MAX-ACCESS read-write
    STATUS current
    DESCRIPTION
        "This MIB object is used to clear the current test
        results of supported conditions indicated by
        'pktcEnEndPntFgnPotSupport'.
        Setting a bit to a value of '1' clears the corresponding
        results in the MIB Object 'pktcEnEndPntFgnTestResults' and
        the validity as indicated by the MIB object
        'pktcEnEndPntFgnTestValidity' for the supported
        conditions only (i.e, the MTA MUST set the corresponding
        bits to a value of '0' in the indicated tables).

```

If an SNMP SET attempts to set a bit corresponding to an unsupported condition to a value of '1', then the MTA MUST reject the entire SNMP SET and report an 'inconsistent value' error.

For all unsupported scenarios, the corresponding bits MUST be set to a value of '0'.

Whenever one or more tests are enabled by the MIB Object 'pktcEnEndPntRunFgnPotTests', the MTA MUST also reset the corresponding bits in this MIB Object to a value of '0'."

```
::= { pktcEnEndPntInfoTableEntry 3}
```

pktcEnEndPntRunFgnPotTsts OBJECT-TYPE

```
SYNTAX BITS {
    runFgnPotentialTsts (0),
    runHazardousPotTsts (1)
}
```

MAX-ACCESS read-write

STATUS current

DESCRIPTION

"This MIB object is used to initiate one or more test cases associated with a supported foreign potential detection.

Thus, whenever one or more BITS corresponding to supported foreign scenario potential detection mechanisms are set to a value of '1', the MTA MUST enable those tests.

Once the tests are executed, the MTA MUST:

- set the corresponding bit to a value of '0'
- update the corresponding BITS in the MIB Objects 'pktcEnEndPntFgnTestValidity' and 'pktcEnEndPntFgnTestResults'.

If an SNMP SET attempts to set a bit corresponding to an unsupported condition to a value of '1', then the MTA MUST reject the entire SNMP SET and report an 'inconsistent value' error.

Whenever a test is being run on an EndPoint the MTA MUST set the corresponding 'ifOperStatus' MIB Object to a value of 'testing(3)' for the whole duration of the test. When the test is completed, the MTA MUST set the ifOperStatus to the value corresponding to the current state of the line.

Note: Whenever multiple tests are run, the ordering of the tests or the results is vendor dependent and need not necessarily follow the ordering of BITS in this MIB Object."

```
::= { pktcEnEndPntInfoTableEntry 4}
```

pktcEnEndPntFgnTestValidity OBJECT-TYPE

```
SYNTAX BITS {
    fgnPotTstValidity (0),
    hazardousPotTstValidity (1)
}
```

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"This MIB object is used to indicate the validity of the corresponding test cases that were initiated using the MIB Object 'pktcEnEndPntRunFgnPotTests'.

An MTA MUST:

- return a value of '1' if the tests were run successfully and the results are valid.
- return a value of '0' if a particular test was not

initiated or if the tests could not be run successfully and hence the results are invalid.

Note: The MTA MUST set all the BITS to '0' as soon as one or more test cases are initiated."

```
::= { pktcEnEndPntInfoTableEntry 5}
```

pktcEnEndPntFgnTestResults OBJECT-TYPE

```
SYNTAX BITS {
    fgnPotentialResults (0),
    hazardousPotResults (1)
}
```

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"This MIB object is used to indicate the results of the corresponding test cases that were initiated using the MIB Object 'pktcEnEndPntRunFgnPotTests'.

An MTA MUST:

- set the corresponding bit to a value of '1' if the tests indicated the presence of a foreign potential as per the associated test case.
- set the corresponding bit to a value of '0' if the tests indicated the absence of a foreign potential as per the associated test case.

Note: The MTA MUST set all the BITS to '0' as soon as one or more test cases are initiated."

```
::= { pktcEnEndPntInfoTableEntry 6}
```

pktcEnNcsEndPntLVMgmtTable OBJECT-TYPE

```
SYNTAX SEQUENCE OF PktcEnNcsEndPntLVMgmtTableEntry
```

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"This MIB table contains the MIB Objects used for managing loop voltage on an MTA. An MTA MUST implement the defined MIB Objects and the associated functionality."

```
::= { pktcEnNcsEndPntConfigObjects 3 }
```

pktcEnNcsEndPntLVMgmtTableEntry OBJECT-TYPE

```
SYNTAX PktcEnNcsEndPntLVMgmtTableEntry
```

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"Each entry in this MIB table consists of the loop voltage management policy for the specified index. The MTA MUST use the ifIndex with a value of '1' to represent the E-MTA and the remaining indices (if used) to represent the endpoints (as specified in [1]).

When the ifIndex is set to a value of '1', it represents a policy that MUST be applied to all the lines on an MTA.

A MTA MUST support access to this MIB Object via the ifIndex set to a value of '1' (i.e., per-device policy). "

REFERENCE "PacketCable Device Provisioning specification [1]"

INDEX { ifIndex }

```
::= { pktcEnNcsEndPntLVMgmtTable 1 }
```

PktcEnNcsEndPntLVMgmtTableEntry ::=

```

SEQUENCE {
    pktcEnNcsEndPntLVMgmtPolicy      INTEGER,
    pktcEnNcsEndPntLVMgmtResetTimer  Unsigned32,
    pktcEnNcsEndPntLVMgmtMaintTimer  Unsigned32
}

pktcEnNcsEndPntLVMgmtPolicy  OBJECT-TYPE
    SYNTAX  INTEGER {
        voltageAtAllTimes(1),
        voltageUnlessRFQAMAbsent(2),
        voltageBasedOnServiceOrTimers(3),
        voltageBasedOnService(4)
    }
    MAX-ACCESS  read-write
    STATUS  current
    DESCRIPTION

        "This MIB Object allows the Service Provider to choose
        a suitable policy for Loop Voltage behavior on MTAs.

        Unless overridden by the operator, the MTA MUST use the
        default value specified in the definition of this MIB
        Object.

        The MTA MUST adhere to PacketCable signaling
        requirements, such as the NCS open loop voltage requirement,
        irrespective of any chosen policy.

        For MTAs that need to remove loop voltage during the MTA
        initialization phase, in contradiction to a chosen policy,
        such a loop voltage removal period MUST NOT exceed 1000ms.

        The MTA MUST retain the value of this MIB Object across
        hard reboots or soft resets (for a definition of the terms,
        please refer to [1]).

        This MIB object specifies four policies. An informative
        illustration of the E-MTA behavior with different policies
        is presented in Appendix A.

        Provisioned line is an MTA Endpoint that has been provided
        with valid per-line configuration data either via the
        configuration file (during provisioning) or the SNMP
        management interface.

```

When the MIB Object is set to a value of  
'voltageAtAllTimes', - indicating Policy 1 -  
the MTA MUST maintain the loop idle voltage on all  
lines, irrespective of the line status.

When this MIB Object is set to a value of  
'voltageUnlessRFQAMAbsent' - indicating Policy 2  
- the MTA MUST apply loop idle voltage at all  
times except when it confirms the absence of any  
RF QAM carrier, following a complete scan of the  
spectrum (i.e., loop voltage is maintained during  
the scan). When the MTA detects the presence of any  
RF QAM carrier, it MUST apply the loop idle voltage.  
Additionally, the following conditions apply:  
- during a hard reboot, this policy applies at all

- lines until the MTA is successfully provisioned (i.e., pktcMtaDevProvisioningState has a value other than 'InProgress')
- once the MTA is successfully provisioned (i.e., pktcMtaDevProvisioningState has a value of 'pass(1)', 'passWithWarnings(4)' or 'passWithIncompleteParsing(5)') then the policy applies to all provisioned lines
- upon the onset of a re-initialization due to a soft reset (via SNMP or Rf conditions) the MTA MUST continue to maintain the existing policy and state on previously provisioned lines, unless overridden by a policy or the provisioning process specifies otherwise

This policy is similar to Policy 1, except for the ability to recognize events like cable cuts (due to malicious activities, or otherwise).

The following requirements apply to policies 3 and 4:

- upon the onset of a re-initialization due to a soft reset the MTA MUST continue to maintain the existing policy and state on provisioned lines, unless overridden by a policy or the provisioning process specifies otherwise
- once the provisioning process is completed with the value of the MIB Object pktcMtaDevProvisioningState set to a value of 'pass(1)', 'passWithWarnings(4)' or 'passWithIncompleteParsing(5)', the MTA MUST apply the chosen policy to all the provisioned lines

When this MIB Object is set to a value of 'voltageBasedOnServiceOrTimers' - indicating Policy 3 - the MTA MUST adhere to the requirements that follow at any given point in time:

- when the timer defined by pktcEnNcsEndPntLVMgmtResetTimer has a non-zero value, the MTA MUST apply loop idle voltage under all circumstances (similar to policy 1). Refer to the definition of the MIB Object for the persistence and timer requirements.
- when the timer defined by pktcEnNcsEndPntLVMgmtMaintTimer has a non-zero value, the MTA MUST maintain a line's loop idle voltage state that was in effect prior to the timer being set to a non-zero value. Refer to the definition of the MIB Object defining the timer for the persistence and timer requirements.
- When the timers defined by pktcEnNcsEndPntLVMgmtMaintTimer and pktcEnNcsEndPntLVMgmtResetTimer have expired (both have a value of zero), then:
  - = the MTA MUST apply loop voltage if the provisioning process is completed with the value of pktcMtaDevProvisioningState set to a value of 'pass(1)', 'passWithWarnings(4)' or 'passWithIncompleteParsing(5)'
  - = During a T4 timeout (note: the timers have expired), the E-MTA MUST remove loop idle voltage on all lines



- When both the timers are active (i.e., they both have non-zero values), then the timer defined by the MIB Object `pktcEnNcsEndPntLVMgmtMaintTimer` takes precedence
- if none of the above cases apply, the MTA MUST remove loop idle voltage on all lines

When the MIB Object is set to a value of 'voltageBasedOnService' - indicating Policy 4 - the following conditions apply at any given point in time:

- the MTA MUST apply loop idle voltage to all the provisioned lines if the value of the MIB Object 'pktcMtaDevProvisioningState' is set to a value of 'pass(1)', 'passWithWarnings(4)' or 'passWithIncompleteParsing(5)'
  - in all other cases, the MTA MUST remove loop idle voltage on all lines."
- REFERENCE "PacketCable Device Provisioning specification [1]"
- DEFVAL { voltageBasedOnService }
- ::= { pktcEnNcsEndPntLVMgmtTableEntry 1 }

`pktcEnNcsEndPntLVMgmtResetTimer` OBJECT-TYPE

SYNTAX Unsigned32 (0..1440)

UNITS "minutes"

MAX-ACCESS read-write

STATUS current

DESCRIPTION

"This MIB Object specifies the time duration allowed for an MTA to successfully provision and is only applicable when the MIB Object `pktcEnNcsEndPntLVMgmtPolicy` is set to a value of 'voltageBasedOnServiceOrTimers'.

In all other cases, the MTA MUST:

- return a value of '0' upon any retrieval requests
- return an error of 'inconsistentValue' upon any modification requests

The value contained by this MIB Object is a countdown timer and the MTA MUST start counting down the configured value only upon a hard reboot, a soft reset or a T4 timeout. Once this timer has reached a value of zero, the MTA MUST retain the value (of zero) until successfully configured otherwise. The MTA MUST use a change in the value of this MIB Object only on the next hard reboot, soft reset or T4 timeout.

The MTA MUST persist the last configured value (i.e., not the countdown value) of this MIB Object across hard reboots and soft resets.

Refer to the MIB Object `pktcEnNcsEndPntLVMgmtPolicy` for usage within 'voltageBasedOnServiceOrTimers'."

DEFVAL { 5 }

::= { pktcEnNcsEndPntLVMgmtTableEntry 2 }

`pktcEnNcsEndPntLVMgmtMaintTimer` OBJECT-TYPE

SYNTAX Unsigned32 (0..1440)

UNITS "minutes"

MAX-ACCESS read-write

STATUS current  
 DESCRIPTION  
 "This MIB Object allows the operator to specify the time that loop voltage condition will be maintained, irrespective of the changes to the MTA. It is only applicable when the MIB Object pktcEnNcsEndPntLVMgmtPolicy is set to a value of 'voltageBasedOnServiceOrTimers'. In all other cases, the MTA MUST:

- return a value of '0' upon any retrieval requests
- return an error of 'inconsistentValue' upon any modification requests

The value contained in this MIB Object is a countdown timer and the MTA MUST start counting down the value immediately after a successful configuration to a non-zero value. Once this timer has reached a value of zero, the MTA MUST retain the value (of zero) until successfully configured otherwise.

The MTA MUST retain the value of this MIB Object (i.e., the countdown value) across soft resets. The MTA MUST reset the value of this MIB Object (to its default value) during a hard reboot of the MTA.

Refer to the MIB Object pktcEnNcsEndPntLVMgmtPolicy for information about applicability and usage."

DEFVAL { 0 }  
 ::= { pktcEnNcsEndPntLVMgmtTableEntry 3 }

```
--
-- The Provisioned Loss Plan Table
--
pktcEnNcsEndPntLossTable OBJECT-TYPE
    SYNTAX      SEQUENCE OF PktcEnNcsEndPntLossEntry
    MAX-ACCESS   not-accessible
    STATUS       current
    DESCRIPTION
        " The E-MTA supports two provisioned loss parameters, one for
          the D/A direction (towards the subscriber) and one for A/D
          direction (from the subscriber) direction. This data table
          represents the loss for each line provided by the E-MTA."
    ::= { pktcEnNcsEndPntConfigObjects 4 }

pktcEnNcsEndPntLossEntry OBJECT-TYPE
    SYNTAX      PktcEnNcsEndPntLossEntry
    MAX-ACCESS   not-accessible
    STATUS       current
    DESCRIPTION
        " The E-MTA supports two provisioned loss parameters, one for
          the D/A direction (towards the subscriber) and one for A/D
          direction (from the subscriber) direction. This data table
          represents the loss for each line provided by the E-MTA.

          Each entry in this data table describes the loss
          for the associated line."
    INDEX       { ifIndex }
    ::= { pktcEnNcsEndPntLossTable 1 }

PktcEnNcsEndPntLossEntry ::=
    SEQUENCE {
        pktcEnNcsEndPntLossDA      Integer32,
        pktcEnNcsEndPntLossAD      Integer32
    }
```

```

pktcEnNcsEndPntLossDA OBJECT-TYPE
    SYNTAX      Integer32 (0..12)
    UNITS       "dB"
    MAX-ACCESS  read-write
    STATUS      current
    DESCRIPTION
        " This object specifies the provisioned loss parameter
          for the D/A direction (towards the subscriber) in dB.

          The E-MTA MUST implement this element per the PacketCable Embedded
          MTA Analog Interface and Powering Specification."
    REFERENCE  "PacketCable AIP Specification"
    DEFVAL     {9}
    ::= { pktcEnNcsEndPntLossEntry 1 }

pktcEnNcsEndPntLossAD OBJECT-TYPE
    SYNTAX      Integer32 (0..6)
    UNITS       "dB"
    MAX-ACCESS  read-write
    STATUS      current
    DESCRIPTION
        " This object specifies the provisioned loss parameter
          for the A/D direction (from the subscriber)in dB.

          The E-MTA MUST implement this element per the PacketCable Embedded
          MTA Analog Interface and Powering Specification."
    REFERENCE  "PacketCable AIP Specification"
    DEFVAL     {3}
    ::= { pktcEnNcsEndPntLossEntry 2 }

--
-- Compliance statements
--
pktcEnSigBasicCompliance MODULE-COMPLIANCE
    STATUS      current
    DESCRIPTION
        "The compliance statement for devices that implement
          PacketCable defined Signaling on an MTA."

    MODULE PKTC-EN-SIG-MIB

--
-- Mandatory groups
--
MANDATORY-GROUPS {
    pktcEnSigGroup
}
GROUP pktcEnNcsGroup
DESCRIPTION
    "This group is mandatory for any MTA implementing
      PacketCable signaling."
GROUP pktcEnNcsLVMgmtGroup
DESCRIPTION
    "This group is mandatory for any MTA implementing
      PacketCable signaling."

::={ pktcEnSigCompliances 1 }

```

```

--
-- Conformance group for common Signaling.
--
pktcEnSigGroup OBJECT-GROUP
    OBJECTS {
        pktcEnNcsMinimumDtmfPayout
    }
    STATUS current
    DESCRIPTION
        "Enhanced group of objects for the common portion of the
        PacketCable Signaling MIB."
    ::= { pktcEnSigGroups 1 }

--
-- Conformance group for NCS Signaling.
--
pktcEnNcsGroup OBJECT-GROUP
    OBJECTS {
        pktcEnNcsEndPntQuarantineState,
        pktcEnNcsEndPntHookState,
        pktcEnNcsEndPntFaxDetection,
        pktcEnEndPntFgnPotSupport,
        pktcEnEndPntFgnPotDescr,
        pktcEnEndPntClrFgnPotTsts,
        pktcEnEndPntRunFgnPotTsts,
        pktcEnEndPntFgnTestValidity,
        pktcEnEndPntFgnTestResults,
        pktcEnNcsEndPntLossDA,
        pktcEnNcsEndPntLossAD
    }
    STATUS current
    DESCRIPTION
        "Enhanced group of objects for the NCS portion of the
        PacketCable Signaling MIB. This is mandatory for
        NCS signaling support."
    ::= { pktcEnSigGroups 2 }

--
-- Conformance group for Loop Voltage Management
--
pktcEnNcsLVMgmtGroup OBJECT-GROUP
    OBJECTS {
        pktcEnNcsEndPntLVMgmtPolicy,
        pktcEnNcsEndPntLVMgmtResetTimer,
        pktcEnNcsEndPntLVMgmtMaintTimer
    }
    STATUS current
    DESCRIPTION
        "Enhanced group of objects for the loop voltage
        Management of PacketCable MTAs based on Signaling
        and configured policies."
    ::= { pktcEnSigGroups 3 }

pktcEnNcsDeprecatedGroup OBJECT-GROUP
    OBJECTS {
        pktcEnNcsEndPntStatusReportCtrl
    }
    STATUS deprecated
    DESCRIPTION
        "This contains a list of deprecated Extension
        Signaling MIB Objects."
    ::= { pktcEnSigGroups 4 }

```

END

## Appendix A Loop Voltage Management Policies

This appendix provides an illustration of the loop voltage management policies defined by the MIB Object `pkcEnNcsEndPntLVMgmtPolicy`. Please note that this is an informative illustration and the MIB Object definition is normative under all circumstances.

Stage	Policy 1	Policy 2	Policy 3	Policy4 (default)
Boot loader initialization following a hard reboot	unspecified	unspecified	unspecified	unspecified
Boot loader initialization following a soft reset	Same status as prior to reset	Same status as prior to reset	Same status as prior to reset	Same status as prior to reset
DOCSIS RF Scan	APPLY voltage on all lines	APPLY for first full pass through spectrum, REMOVE if no QAM lock occurred; REAPPLY if QAM returns	APPLY until Maintenance Timer and Voltage Reset Timeout expire; REMOVE thereafter	REMOVE voltage
eCM Ranging/Registering	APPLY	APPLY	Same status as final state from scanning; REMOVE if timers expire;	REMOVE
eCM provisioning process	APPLY	Same status as final state from scanning	Same status as final state from scanning; REMOVE if timers expire	REMOVE
Loss of Rf signal prior to T4	APPLY	APPLY	APPLY	APPLY
DOCSIS Rf scanning after T4	APPLY	APPLY for first full pass through spectrum, REMOVE if no QAM lock occurred; REAPPLY if QAM returns	APPLY until timers expire, REMOVE thereafter	REMOVE
eMTA provisioning (MTA1 onwards, while <code>pkcMtaDevProvisioningState</code> is set to a value of 'inProgress')	APPLY	Same status as final state from Rf scanning	APPLY until timers expire, REMOVE thereafter	REMOVE
E-MTA is operational and the eMTA MIB Object <code>pkcMtaDevProvisioningState</code> is set to a value of 'pass', 'passWithWarnings' or 'passWithIncompleteParsing'	APPLY	APPLY	APPLY	APPLY

Stage	Policy 1	Policy 2	Policy 3	Policy4 (default)
E-MTA is operational, the eMTA provisioning is completed, but the MTA's MIB Object pktcMtaDevProvisioningState is set to a value *other than * 'pass', 'passWithWarnings' or 'passWithIncompleteParsing'	APPLY	APPLY	APPLY until timers expire, REMOVE thereafter	REMOVE

## Appendix B Acknowledgements

On behalf of CableLabs and its participating member companies, we would like to extend our thanks to all those who contributed to the development of this specification. Certainly all the participants of the provisioning focus team have added value to this effort by participating in the review and weekly conference calls. Particular thanks are given to:

Rodney Osborne (Arris Interactive)

Rick Morris (Arris Interactive)

Eugene Nechamkin (Broadcom Corp.)

Jean-Francois Mule, Sumanth Channabasappa, Venkatesh Sunkad, John Berg (CableLabs, Inc.)

Satish Kumar (Texas Instruments)

Kevin Marez (Motorola, Inc.)

Philip Freyman (Motorola, Inc.)

*Eduardo Cardona (CableLabs, Inc.)*



## Appendix C Revision History

The following ECN has been incorporated into PKT-SP-MIB-EXSIG1.5-I02-050812.

ECN	ECN Date	Summary
MIB-EXSIG1.5-N-05.0278-1	7/11/05	MAX-ACCESS alignment of the MIB Objects 'pkcEnNcsEndPntFaxDetection' and 'pkcEnNcsEndPntStatusReportCtrl'

The following ECN has been incorporated into PKT-SP-MIB-EXSIG1.5-I03-070412.

ECN	ECN Date	Summary
MIB-EXSIG1.5-N-07.0396-5	3/19/2007	EMTA Loop Voltage Management Feature Description

The following ECN has been incorporated into PKT-SP-MIB-EXSIG1.5-I04-090624.

ECN	ECN Date	Summary
MIB-EXSIG1.5-N-09.0569-2	6/15/2009	MIB module nits corrections

The following ECN has been incorporated into PKT-SP-MIB-EXSIG1.5-I05-121030.

ECN	ECN Date	Summary
MIB-EXSIG1.5-N-12.0689-2	8/13/12	Plant Loss configuration requirements for E-MTA